

--	--	--	--	--	--	--	--	--	--

**Fifth Semester B.E. Degree Examination, Dec.2018/Jan.2019**  
**Signals and Systems**

Time: 3 hrs.

Max. Marks:100

**Note: Answer any FIVE full questions, selecting  
atleast TWO questions from each part.**

**PART – A**

- 1 a. Define a signal and a system with examples. (04 Marks)
- b. Sketch the following signal and determine even and odd components.  

$$x(n) = (1, 2, 0, 1, 2)$$

$\uparrow$

(06 Marks)
- c. Find the total energy of the signal :  

$$x(t) = A ; -\frac{T}{2} \leq t \leq \frac{T}{2}$$

$$= 0 ; \text{ otherwise}$$
(04 Marks)
- d. Check whether the following signals are periodic or not. If periodic determine their fundamental period.  
(i)  $x(t) = \cos t + \sin \sqrt{2} t$   
(ii)  $x(n) = \cos (\pi + 0.2n)$ 
(06 Marks)
- 2 a. Determine whether the system given below is (i) memoryless (ii) Causal (iii) Time invariant (iv) Linear (v) stable  

$$y(t) = e^{-x(t)}$$
(06 Marks)
- b. Find the response of an L.T.I. system with impulse response  $h(n) = \alpha^n u(n)$  for an input signal  $x(n) = \beta^n u(n)$ ;  $|\alpha| < 1$  and  $|\beta| < 1$ . When (i)  $\alpha \neq \beta$  and (ii)  $\alpha = \beta$ . (10 Marks)
- c. Find the step response for the system whose impulse response  $h(t) = t u(t)$ . (04 Marks)
- 3 a. The impulse response of a system is  $h(t) = e^{2t} u(t - 1)$ . Check whether the system is (i) stable (ii) causal (iii) memoryless. (06 Marks)
- b. The differential equation of the system is given as,  $\frac{d^2y(t)}{dt^2} + \frac{3dy(t)}{dt} + 2y(t) = x(t)$   
with  $y(0) = 1$ ,  $\left. \frac{dy(t)}{dt} \right|_{t=0} = 1$   
Determine total response of the system for an input  $x(t) = u(t)$ . (08 Marks)
- c. Draw the direct form-I and direct form-II realizations for the system  

$$y(n) - \frac{1}{2}y(n-1) + \frac{1}{4}y(n-2) = x(n) + 2x(n-1)$$
(06 Marks)
- 4 a. State and prove the following properties of discrete time fourier series:  
(i) Parseval theorem  
(ii) Time shift (10 Marks)
- b. Find the fourier series co-efficients for the periodic signal  $x(t)$  with period, 2 sec given by  $x(t) = e^{-t}$ ; for  $-1 \leq t \leq 1$ . (10 Marks)

**PART – B**

- 5 a. State and prove the following properties of continuous time fourier transform :  
 (i) Convolution (ii) Linearity (10 Marks)
- b. Find the fourier transform of the following :  
 $x(t) = \sin(\pi t) e^{-2t} u(t)$  (05 Marks)
- c. Find the inverse fourier transform of  $X(\omega) = \frac{j\omega + 12}{(j\omega)^2 + 5j\omega + 6}$  (05 Marks)
- 6 a. Find the DTFT of the following signals :  
 (i)  $x(n) = \left(\frac{1}{2}\right)^n u(n-2)$   
 (ii)  $x(n) = u(n) - u(n-6)$   
 (iii)  $x(n) = 2^n u(-n)$  (10 Marks)
- b. Obtain the frequency response and impulse response of the system having the output  $y(n)$  for the input  $x(n)$  as given below:  
 $x(n) = \left(\frac{1}{2}\right)^n u(n)$   
 $y(n) = \frac{1}{4} \left(\frac{1}{2}\right)^n u(n) + \left(\frac{1}{4}\right)^n u(n)$  (10 Marks)
- 7 a. State and prove the following properties of z-transform:  
 (i) Initial value theorem (08 Marks)  
 (ii) Differentiation in z-domain
- b. Find the Z.T. of the following and sketch the R.O.C.S.  
 (i)  $x(n) = a^{n-1} u(n)$   
 (ii)  $x(n) = \left(\frac{1}{2}\right)^n u(n) + 2^n u(-n-1)$  (06 Marks)
- c. Find the inverse z-transform of  $X(z) = \frac{z^2 - 3z}{z^2 + \frac{3}{2}z - 1}$  using partial fraction expansion method,  
 ROC :  $\frac{1}{2} < |z| < 2$ . (06 Marks)
- 8 a. A causal discrete time LTI system is described by  
 $y(n) - \frac{3}{4}y(n-1) + \frac{1}{8}y(n-2) = x(n)$   
 where  $x(n)$  and  $y(n)$  are the input and output of the system respectively.  
 (i) Determine the system function  $H(z)$   
 (ii) Find the impulse response  $h(n)$   
 (iii) Find the stability of the system (12 Marks)
- b. Solve the following difference equation for the given initial conditions and input.  
 $y(n) - \frac{1}{9}y(n-2) = x(n-1)$   
 with  $y(-1) = 0$ ,  $y(-2) = 1$  and  $x(n) = 3u(n)$ . Use unilateral z-transformation. (08 Marks)

\*\*\*\*\*