

OR

The crank radius of a reciprocating engine is 90mm. The connecting rod is 360mm long and the crank rotates at 150rpm clockwise. Determine the velocity and acceleration of piston and angular velocity and angular acceleration of connecting rod. When the angle made the crank (20 Marks) with IDC is 30°. The Klein's construction for solution.

Module-4

- Derive following with a neat sketch. 7 a.
 - i) Pitch circle diameter
 - ii) Modules
 - iii) Addendum and dedendum
 - iv) Path of contact and arc of contact
 - v) Pressure angle
 - b. Two four gear wheels have 24 and 30 teeth and the standard addendum of 1 module. The pressure angle is 20°. Calculate the path of contact and arc of contact. (10 Marks)

OR

- Name different types of gear trains. Explain any one gear train with a neat sketch. (08 Marks) 8 The Fig Q8(b) shows an epicyclic gear train where the arm 'A' is the driver and the annular a.
 - gear D. is the follower. The wheel D has 1/2 teeth and B has 48 teeth. B runs freely on P and b. D is separately driven. The arm 'A' runs at 100 rpm and wheel D at 50 rpm in same direction. Find the torque on B is A receives 7.5 kW.



(12 Marks)

Module-5

Define : 9 a.

10

(04 Marks) i) Base circle and prime circle ii) Angle of ascent and decent A cam of base circle radius 50mm is to operate Q roller follower of 20mm diameter the b. follower is to have SHM. The speed of the cam is 360° clockwise. Draw the cam provide for the cam lift of 40mm. Angle of ascent = 60° , angle of dwell = 40 angle of descent = 90° followed by dwell again. Also calculate maximum velocity and acceleration during ascent (16 Marks) and descent.

OR

A cam rotating clockwise at uniform speed of 300rpm operates a reciprocating follower through a roller 1.5cm diameter. The follower motion is defined as follows :

- i) Outward during 150° with UARM
- ii) Dwell for next 30°
- iii) Return during next 120° with SHM
- iv) Dwell for the remaining permit

Stroke of the follower is 3cm, minimum radius of the cam is 3cm. Draw the cam proving. (20 Marks)

2 of 2

(10 Marks)

6