

OR

- 6 a. Let $x(n)$ be the 8-point sequence of $x(n) = \left\{ \frac{1}{\sqrt{2}}, 1, \frac{1}{\sqrt{2}}, 0, \frac{-1}{\sqrt{2}}, -1, \frac{-1}{\sqrt{2}}, 0 \right\}$. Compute the DFT of the sequence using DIT FFT algorithm. (06 Marks)
- b. What is Chirp-Signals and mention the applications of Chirp-Z-transform? (04 Marks)
- c. A designer is having a number of 8-point FFT chips. Show explicitly how he should interconnect three chips in order to compute a 24-point DFT. (06 Marks)

Module-4

- 7 a. Design a digital low pass Butterworth Filter using bilinear transformation to meet the following specifications:
 $-3 \text{ dB} \leq |H(e^{j\omega})| \leq -1 \text{ dB}$ for $0 \leq \omega \leq 0.5\pi$
 $|H(e^{j\omega})| \leq -10 \text{ dB}$ for $0.7\pi \leq \omega \leq \pi$ (10 Marks)
- b. Obtain the parallel form of realization of a system difference equation,
 $y(n) = 0.75y(n-1) - 0.125y(n-2) + 6x(n) + 7x(n-1) + x(n-2)$ (06 Marks)

OR

- 8 a. Convert the analog filter with system function,
 $H_a(s) = \frac{s+0.1}{(s+0.1)^2 + 9}$ into a digital IIR filter by means of the impulse invariance method. (08 Marks)
- b. Obtain the DF-I and cascade form of realization of the system function,

$$H(z) = \frac{1 + \frac{1}{3}z^{-1}}{\left(1 - \frac{1}{5}z^{-1}\right)\left(1 - \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}\right)}$$
 (08 Marks)

Module-5

- 9 a. Obtain the linear phase realization of FIR filter with impulse response,
 $h(n) = \delta(n) - \frac{1}{2}\delta(n-1) + \frac{1}{4}\delta(n-2) + \frac{1}{4}\delta(n-3) - \frac{1}{2}\delta(n-4) + \delta(n-5)$. (06 Marks)
- b. What are the advantages and disadvantages of the window technique for designing FIR filter? (04 Marks)
- c. A low pass filter is to be designed with the following desired frequency response:

$$H_d(e^{j\omega}) = \begin{cases} e^{-j2\omega}, & |\omega| < \frac{\pi}{4} \\ 0, & \frac{\pi}{4} < |\omega| < \pi \end{cases}$$

Determine the filter coefficients $h_d(n)$ and $h(n)$ if $\omega(n)$ is a rectangular window defined as,

$$\omega_R(n) = \begin{cases} 1, & 0 \leq n \leq 4 \\ 0, & \text{Otherwise} \end{cases}$$
 (06 Marks)

OR

- 10 a. The desired frequency response of a low pass filter is given by,

$$H_d(e^{j\omega}) = \begin{cases} e^{-j3\omega}, & |\omega| < \frac{3\pi}{4} \\ 0, & \frac{3\pi}{4} < |\omega| < \pi \end{cases}$$
 Determine the frequency response of the FIR filter if

Hamming window is used with $N = 7$. (10 Marks)

- b. Realize an FIR filter with impulse response $h(n)$ given by,

$$h(n) = \left(\frac{1}{2}\right)^n [u(n) - u(n-4)]$$
 using direct form. (06 Marks)