

--	--	--	--	--	--	--

**Sixth Semester B.E. Degree Examination, May/June 2010**  
**Switchgear and Protection**

Time: 3 hrs.

Max. Marks:100

**Note: Answer any FIVE full questions, selecting  
at least TWO questions from each part.**

**PART – A**

1.
  - a. Explain the cut – off characteristics and time-current characteristics of a fuse. (06 Marks)
  - b. With a neat sketch, explain the construction and working of a high voltage liquid type fuse. (06 Marks)
  - c. Discuss the recovery rate theory and energy balance theory of arc interruption in a.c. circuit breaker. (08 Marks)
2.
  - a. Explain the phenomenon of current chopping in a circuit breaker. (06 Marks)
  - b. What is resistance switching? Derive the expression for critical resistance interns of system inductance and capacitance, which gives no transient oscillation. (08 Marks)
  - c. In a 132 kV system, reactance and capacitance up to the location of the circuit breaker are  $5 \Omega$  and  $0.02 \mu\text{F}$  respectively. A resistance of  $500 \Omega$  is connected across the circuit breaker. Determine : i) Natural frequency of oscillation ; ii) Damped frequency of oscillation and iii) Critical value of resistance. (06 Marks)
3.
  - a. With a neat figure, explain the construction and working of an axial flow air – blast circuit breaker. (08 Marks)
  - b. Discuss, resistance switching in air – blast circuit breaker. (06 Marks)
  - c. Explain the following terms with respect to  $\text{SF}_6$  gas i) Electronegativity and ii) Arc time constant. (06 Marks)
4.
  - a. With a neat figure, explain the construction of an outdoor minimum – oil circuit – breaker. (06 Marks)
  - b. Discuss, direct testing of a circuit breaker. (08 Marks)
  - c. With a circuit diagram and waveform, explain synthetic testing an HV circuit breaker. (06 Marks)

**PART – B**

5.
  - a. What is a protective relay? Discuss the basic requirements of protective relaying. (08 Marks)
  - b. Explain concept of zones of protection used in protection of large power systems. (06 Marks)
  - c. Differentiate between IDMT overcurrent relay and extremely inverse – time overcurrent relay characteristics. (06 Marks)
6.
  - a. Explain the construction and working of a Buchholz relay. (06 Marks)
  - b. Determine the actual time of operation of a 5 ampere, 3 second over current relay having a current setting of 125% and a time setting multiplier of 0.6 connected to supply circuit through a 400/5 current transformer when the circuit carries a fault current of 4000 A. Time of operation is 3.5 seconds for the estimated value of PSM. (06 Marks)
  - c. Explain stepped time-distance characteristics of three distance relaying units used for I, II and III zones of protection. (08 Marks)
7.
  - a. With the basic circuit diagram, explain harmonic restraint relay protection for a transformer. (10 Marks)
  - b. Describe the loss of excitation protection in a generator and its characteristics. (10 Marks)
8. Write short notes on :
  - a. Microprocessor based overcurrent relay
  - b. Vacuum circuit breaker
  - c. Restricted earth – fault protection in a transformer
  - d. Fuse and fuse materials. (20 Marks)