2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8=50, will be treated as malpractice Important Note: 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.

Seventh Semester B.E. Degree Examination, Dec.2019/Jan.2020 **Mechanical Vibration and Vehicle Dynamics**

Time: 3 hrs. Max. Marks: 100

Note: Answer any FIVE full questions, selecting atleast TWO questions from each part.

PART - A

- a. Define the following:
 - i) Forced vibration.
 - ii) Simple harmonic motion.
 - iii) Degree of freedom.

(06 Marks)

b. Add the following motion analytically and check the solution graphically

 $x_1 = 2 \cos(wt + 0.5)$, $x_2 = 5 \sin(wt + 1.0)$.

(14 Marks)

- a. Using Newton's method and Energy method, derive equation of motion and natural 2 frequency of vibration of a spring mass system in vertical position. (10 Marks)
 - b. Determine the natural frequency of simple pendulum:
 - i) Neglecting the mass of rod
 - ii) Considering the mass of rod [Newton's method].

(10 Marks)

- a. The mass of a single degree damped vibrating system is 7.5kg makes 24 free oscillation in 3 14 secs, when distributed from its equilibrium position. The amplitude of vibration reduces 0.25 of its initial value after 5 oscillations. Determine
 - i) Stiffness of spring.
 - ii) Log. Decrement.
 - iii) Damping factor.

(10 Marks)

- b. A spring mass dashpot system is given an initial velocity of XW_n where W_n is the undamped natural frequency of the system. Find equation of motion for the system when
 - $\xi = 2.5$
- ii) $\xi = 1$.

(10 Marks)

- a. Define Transmissibility. Derive an expression for motion transmissibility.
 - b. A mass of 10kg suspended from one end of helical spring, the other end is fired. The stiffness of spring is 10N/mm. The viscous damping causes the amplitude to decrease 1/10th of initial value in four complete oscillations. If a periodic force of 150cos50t N is applied at mass with vertical direction. Find the amplitude of forced vibration, what is its value at (10 Marks) resonance?

PART - B

- a. Explain and discuss vibrometer and accelerometer devices with the help of relative 5 amplitude ratio versus frequency ratio plot. (10 Marks)
 - b. Obtain an expression for whirling of shaft with air damping.

(10 Marks)

6 A two degrees of freedom vibrating system is shown in fig. Q6. Determine

i) Two Natural frequencies of vibrations.

ii) Ratio of amplitudes of motion m₁ and m₂ for the two modes of vibration.


iii) Modal vector and modal shapes.

iv) Locate the nodes for each mode of vibration.

Given $m_1 = 2kg$, $m_2 = 1kg$, $k_1 = 40N/m$, $k_2 = 20N/m$.

(20 Marks)

Fig. Q6




7 Fig. Q7, shows the diagram of an automobile. Determine the normal modes of vibration, if the automobile is simulated by the simplified two degrees of freedom system with the following numerical values.

m=1,500~kg , $\ell_1=1.35m$, $\ell_2=1.65m$, $\ell=3m$, k=1.2m , $k_1=35\times 10^3~N/m$, $k_2=40\times 10^3~N/m$

(20 Marks)

Fig. Q7



8 Using Stodola's method, determine the lowest natural frequency of the branched system shown in fig.Q8. (20 Marks)

Fig. Q8

