

USN

--	--	--	--	--	--	--	--	--	--

17EC71

## Seventh Semester B.E. Degree Examination, Feb./Mar. 2022 Microwaves and Antennas

Time: 3 hrs.

Max. Marks: 100

Note: Answer any FIVE full questions, choosing ONE full question from each module.

### Module-1

- 1 a. With neat diagrams, explain the concept of reflex system. (10 Marks)  
b. Calculate the transit time at the cavity gap, transit angle and velocity of electron leaving the gap for 2-cavity klystron that operates at 4GHz with a DC beam voltage of 5kV and 2mm cavity gap. (06 Marks)  
c. Define VSWR. (04 Marks)

OR

- 2 a. Obtain the transmission line equations from fundamentals. (10 Marks)  
b. A transmission line has a resistance of  $2\Omega/m$  with an inductance value of  $8n H/m$ . The conductance of the line is  $0.5m mho/m$  and capacitance is  $0.23p.F$ .  $f = 1GHz$ . Find the characteristics impedance of the line and the propagation constant. (04 Marks)  
c. What is a Smith chart? Explain the different measurement that can be determined using a smith chart? (06 Marks)

### Module-2

- 3 a. Explain the properties of S parameters as applicable to a microwave network. (10 Marks)  
b. Write short notes on :  
i) Coaxial connectors and adapters  
ii) Attenuators. (10 Marks)

OR

- 4 a. What is a Magic Tee? Explain its properties. Also determine its S-matrix. (10 Marks)  
b. Explain a directional coupler and write its S-matrix. (10 Marks)

### Module-3

- 5 a. A certain microstripline has the following parameters.  
 $\epsilon_r = 5.23$   $h = 7$  mils  $t = 2.8$  mils  $w = 10$  mils [Note : 1mil = 0.0254mm]. Calculate the characteristic impedance of line ( $Z_0$ ). (04 Marks)  
b. Explain a parallel strip line, with neat diagram and relevant equations. (06 Marks)  
c. Define the following :  
i) Radiation Intensity  
ii) Aperture of Antenna  
iii) Beam area  
iv) Directivity  
v) Reduction pattern. (10 Marks)

OR

- 6 a. Derive Friis transmission formula. (08 Marks)  
b. Compute the power received by an antenna in case of transmission over a distance of 150km at 500MHz. When gain G of antennas used are both 25dB. ( $P_T = 200W$ ). (06 Marks)  
c. Obtain a relationship between directivity and effective aperture. (06 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and/or equations written eg. 42+8 = 50, will be treated as malpractice.

**Module-4**

- 7 a. Plot the field pattern for an array of 2 isotropic sources with equal amplitude and same phase. Take  $d = \lambda/2$ . (07 Marks)
- b. Find Directivity of a source with a sine squared pattern (doughnut) (power pattern). (07 Marks)
- c. State and explain power theorem. (06 Marks)

OR

- 8 a. Obtain the field pattern for a linear uniform array of isotropic antennas for  $n = 6$ ,  $d = \frac{\lambda}{2}$ ,  $\theta = -d_r$ . (08 Marks)
- b. Obtain an expression for radiation resistance of a short dielectric dipole. (06 Marks)
- c. Define and explain the principle of pattern multiplication. (06 Marks)

**Module-5**

- 9 a. From fundamentals obtain the radiation resistance of a small loop antenna. (08 Marks)
- b. For a horn antenna, explain the horn antenna optimum dimensions. Explain with an example. (06 Marks)
- c. Explain the principle of working of a parabolic Reflector antenna. (06 Marks)

OR

- 10 a. Define helix geometry. Explain the practical design considerations for the monoflex axial mode helical antenna. (06 Marks)
- b. Explain the principle of a Yagi Uda Array Antenna. (08 Marks)
- c. Calculate the directivity of a horn antenna with  $a_e \lambda = 10\lambda$   $a_H = 9\lambda$  (06 Marks)

\* \* \* \* \*