

| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|

Seventh Semester B.E. Degree Examination, Jan./Feb. 2023 Microwave and Antennas

Time: 3 hrs.

Max. Marks: 80

**Note: 1. Answer any FIVE full questions, choosing ONE full question from each module.
2. Use of Smith Chart is permitted.**

Module-1

- 1 a. Explain the Reflex Klystron operation with mode. (06 Marks)
 b. Derive the expression for reflection coefficient and transmission coefficient. (06 Marks)
 c. List the characteristics of Smith Chart. (04 Marks)

OR

- 2 a. A line of $Z_0 = 400\Omega$ is connected to a load of $200 + j300\Omega$ which is excited by matching generator at 800MHz. Find the location and length of a single stub nearest to the load to produce impedance match. Make use of Smith Chart and show all the values. (08 Marks)
 b. A transmission line has the following parameters:
 $R = 2\Omega/m$ $G = 0.5\text{mho/m}$ $f = 1\text{GHz}$ $L = 8\text{nH/m}$ $C = 0.23\text{PF}$.
 Calculate the: i) Characteristic impedance ii) Propagation constant. (04 Marks)
 c. With neat block diagram, explain the typical microwave system. (04 Marks)

Module-2

- 3 a. Illustrate the following s-parameter properties i) Symmetry of [s] for a reciprocal network
 ii) unitary property for lossless junction. (08 Marks)
 b. List the characteristics of Magic Tees along with s-matrix relation. (08 Marks)

OR

- 4 a. List the significance of following microwave passive device: i) Attenuators ii) Phase shifter. (04 Marks)
 b. The S-parameter of a two-port network are given by
 $S_{11} = 0.2\angle 0^\circ$, $S_{22} = 0.1\angle 0^\circ$, $S_{12} = 0.6\angle 90^\circ$, $S_{21} = 0.6\angle 90^\circ$
 Prove that i) The network is reciprocal but not lossless ii) Find the return loss at port 1 when port 2 is short circuited. (04 Marks)
 c. Explain E-plane tee and H-plane tee along with s-matrix relation. (08 Marks)

Module-3

- 5 a. A lossless parallel strip line has a conducting strip width W. The substrate dielectric separating the two conducting strips has a relative dielectric constant ϵ_{rd} of 6 and a thickness d of 4mm.
 Calculate:
 i) The required width W of the conducting strip in order to have a characteristic impedance of 50Ω .
 ii) The strip-line capacitance.
 iii) The strip-line inductance.
 iv) The phase velocity of the wave in the parallel strip line. (04 Marks)
 b. Define the following related to antenna parameter i) Directivity ii) Radiation intensity. (05 Marks)
 c. Derive the expression for effective-aperture and directivity of linear dipole $\lambda/2$ antenna. (07 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.
 2. Any revealing of identification, appeal to evaluator and/or equations written eg, 42+8 = 50, will be treated as malpractice.

OR

- 6 a. Briefly discuss losses in microstrip line. (03 Marks)
- b. A radio link has a 15-W transmitter connected to an antenna of 2.5m^2 effective aperture at 5GHz. The receiving antenna has an effective aperture of 0.5m^2 and is located at a 15-km line of sight distance from the transmitting antenna. Assuming lossless, matched antennas, find the power delivered to the receiver. (04 Marks)
- c. Calculate the directivity of the source with the pattern $u = U_m \sin\theta \sin^3\phi$ using
i) Exact method ii) Approximate method. Choose $0 \leq \theta \leq \pi$ and $0 \leq \phi \leq \pi$. (06 Marks)
- d. Explain Antenna field zones with schematic. (03 Marks)

Module-4

- 7 a. Obtain the expression for the field pattern of two isotropic point source with equal amplitude and equal phase. Assume distance between two source is $\lambda/2$. Also draw the field pattern. (08 Marks)
- b. Show that radiation resistance of short electric dipole is given by $80\pi^2 L_\lambda^2$. (08 Marks)

OR

- 8 a. Derive an array factor expression in case of linear array of n-isotropic point source of equal amplitude and spacing. (08 Marks)
- b. Starting from electric and magnetic potential, obtain far field components for short electric dipole. (08 Marks)

Module-5

- 9 a. Determine the length L, H-plane aperture and flow angle θ_E and θ_H of a pyramidal horn for which E-plane aperture $a_E = 10\lambda$. The horn is fed by a rectangular waveguide with TE_{10} mode. Let $\delta = 0.2\lambda$ in the E plane and 0.375λ in the H-Plane. Also calculate its beam widths and directivity. (06 Marks)
- b. Discuss the constructional details of Log-periodic antenna. (04 Marks)
- c. Derive the field expression for small loop antenna. (06 Marks)

OR

- 10 a. Explain the constructional details of yagi-uda array. (03 Marks)
- b. Derive the expression for radiation resistance of circular loop of any radius say 'a'. (06 Marks)
- c. Obtain the expression for instantaneous electric field and magnetic field at a large distance r from a loop of any radius 'a'. (07 Marks)
